

Central Glass & Ceramic Research Institute
KOLKATA (WEST BENGAL) INDIA
CORRIGENDUM

REFERENCE NO. :- P/NC/323/DK/SO(SB)/OTE/20-21

DATE: 25/03/2021

NAME OF EQUIPMENT: DEVELOPMENT AND SUPPLY OF INTERFACE BOARD FOR CCD BASED FBG INTERROGATION

NOTE: The Bids must be submitted in the Central Public Procurement Portal (URL:<https://etenders.gov.in/eprocure/app>) only. Manual/Offline bids shall not be accepted under any circumstances. Bidders should quote in INR only.

CONSEQUENT TO THE PRE-BID MEETING HELD ON 12/03/2021, THE REVISED SPECIFICATION IS GIVEN BELOW:-

SPECIFICATIONS:-

Details of Items*	Quantity
<p>1.End Use :R&D consumable at CGCRI</p> <p>2. Detailed specification:</p> <p>Development and Supply of Interface Board for CCD based FBG Interrogator (CCD based OEM module will be supplied by CGCRI)</p> <p><i>[Hardware modules along with GUI(source code included in Python/C#) and FPGA project file(source code included in VHDL/Verilog) are to be delivered]</i></p> <ul style="list-style-type: none"> • Compatibility required with both 256px and 512px CCDOEM • No. of multiplexed FBG Sensors to be monitored : 16 • Wavelength Repeatability / Accuracy: +/- 5pm • Resolution: 16 bit • Scan Speed: 3KHz • Clock Speed for driving: 5MHz • Exposure time : 10 to 200000 clock cycles (should be configurable from GUI software) • Communication interface: Ethernet • Noise Level: less than -60dBm • Operational Endurance: Reliability of 24X7 continuous operation for at-least 1 year • Power Supply: 5VDC • Operating Temperature :≤10°C to ≥40°C • Storage Temperature :≤0°C to ≥65°C <p>3. Scope of supply & incidental services:Opto-Electronic Componentmanufacturer matching the conditions of Annex 2 , servicing required for three years</p> <p>4. Inspection and Tests required:Yes</p> <p>5.Acceptance test: verification of the component as per specifications</p> <p>6.Qualification criteria if any:Items should match with the stated specifications</p> <p>Note: detailed specifications in Annexure 1</p>	5no.s


R. RAY
 CONTROLLER OF STORES & PURCHASE
 CGCRI - CENTRAL GLASS & CERAMIC RESEARCH INSTITUTE
 106, एम. टी. रोड, कोलकाता - 700 032

Annexure 1
Detail description of work

1. Scope

Scope of this project to develop an interface card for CCD based OEM Spectrometer (that will be supplied by CGCRI) to read linear detector array and send pixel data over Ethernet interface. Interface Board may be planned as two separate boards namely a Sensor Carrier Board and FPGA Board.

2. Product details and Requirements by CGCRI

An Interface board is to be developed for CCD based OEM interrogator that uses standard InGaAs Sensor array. The board is intended to use for converting analog pixel data to digital and send the digital pixel data to an external device through Ethernet.

Feature / Parameter of Interface card	Specifications
1. Communication Interface	Ethernet (1 Gbps)
2. Clock Frequency	Fixed, 5 MHz
3. Configurable features	Exposure Time <ul style="list-style-type: none"> ▪ (Pulse width & Delay time) User configurable ADC parameters <ul style="list-style-type: none"> ▪ ADC Gain ▪ ADC Offset voltage

3. Model Architecture for Interface board

The model solution is based on a Sensor Carrier Board to mount CCD based OEM and ADC. This board is responsible for interfacing with the sensor array and provides control signals like clock, RESET etc. It also interfaces with ADC that converts the analog pixel data from the sensor. The digital data from the ADC card, is then packetized and sent through 1 Gbit Ethernet in TCP/IP format by the FPGA board.




Figure 3: Interface Board Functional Block Diagram

Ray
 25/3/24
R. R. RAY
 CONTROLLER OF STORES & PURCHASE
 CGCRI - CENTRAL GLASS & CERAMIC RESEARCH INSTITUTION
 100, Rama. Var. Rd., Mohali - 140, 146, J.C. ROAD, 140001
 MOBILE: 9814011000 / 9814011001

The following are the functionalities of FPGA Board:

- Communicate with InGaAs detector array through GPIO as per its protocol.
 - a. Generate digital signals such as ADC clock, 'Exposure Time' signal, Reset Signal.
- Communicate with ADC through serial interface.
- Read parallel data lines from ADC at specific intervals
- Packetize the ADC data as per Ethernet frame format
- Send the digital pixel data to an external device through Ethernet interface.
- Retrieve following 'configurable parameters' from Ethernet data frame received from an external device.
 - Exposure Time
 - ADC parameters like user programmable gain & user programmable offset voltage
- Perform configuration settings as per the commands received through Ethernet.
- Communicate with external device through UART interface for configuring Ethernet IP & Port as an initial set up.
- UDP will be used as the protocol for Ethernet communication.

Detector Array Description:

The detector is an array of 256 or 512 pixels of InGaAs linear image sensors which is referred to as CCD 256OEM (for 256 pixel version) and CCD 512OEM (for 512 pixel version). These OEM modules have one fiber optic input and 22 electrical pins. The main control signals are:

1.	CLK	: 5MHz digital Input
2.	RESET	: Digital Input Pulse
3.	AD_sp	: Digital Output Pulse
4.	AD_trig	: Digital Output Pulse
5.	VIDEO	: Analog Pixel Data Output

CLK: The OEM module has to be driven with a high speed clock of 50% duty cycle. The frequency of the clock signal can be 5MHz.

RESET: This is a Digital Pulse in sync with the CLK signal. The RESET is high for an integral number of CLK cycles and Low for another integral number of CLK cycles. When the pulse is high, the pixels absorb photons from the optical input and this duration is called the Exposure Time or Integration Time.

AD_sp & AD_trig: After the Reset Signal is made Low, after a few CLK cycles, the OEM gives out a digital pulse signal AD_sp spanning several CLK cycles. This marks the starting pulse for pixel read out. After the AD_sp pulse ends, with every CLK cycle, the OEM gives out a narrow pulse on the AD_trig pin.

VIDEO: After the AD_sp pulse ends with every CLK cycle, the OEM gives out an analog voltage corresponding to each pixel in the pixel array of the OEM on the VIDEO pin. This is captured on an ADC and the digitized data has to be stored for each pixel. This set of 256 or 512 pixel data is called a 'Frame'.

Ray
25/3/23
R. Ray
CONTROLLER OF STORES & PURCHASE
CENTRAL GLASS & STAINING RESEARCH INSTITUTE
140, 2ND FLOOR, 1ST STAGE, 3RD CROSS, HALASIA ROAD
BANGALORE | INDIA - 560015

